

FreeSpeak II-24 Beltpack

FreeSpeak II Wireless Solutions



Key Features and Benefits

- Over 1400ft range in good radio conditions
- 1.9 and 2.4GHz beltacks operate on a single system
- Up to 65 – 90 beltacks on a single system
- “Listen Again” message replay
- Simple 2-channel partyline operation to 5-channel intercom on the same beltack
- Over-the-air beltack registration
- 18+ hour battery life or USB port for continuous operation
- XLR-4M, XLR-5F or XLR-7M headset connector options
- IP-65 rating for wet and dusty conditions
- Built-in flashlight



FreeSpeak II is a high performance wireless solution operating in the 1.9 and 2.4GHz frequency bands designed for extensive communication in large-scale operations.

Description

FreeSpeak II is a high performance wireless solution operating in the 1.9 and 2.4GHz frequency bands designed for extensive communication in large-scale operations.

Operation

The FSII-BP24 can connect to the FreeSpeak II base station or to Eclipse HX card frame matrices using the E-QUE-HX interface card. FSII-BP24 users can roam seamlessly between FSII-TCVR-24 antennas over wide areas. The “Listen Again” feature allows users to replay earlier commands, eliminating the need to repeat communication or disturb productions. FSII-BP24 have continuous reception over a 1400ft range in good radio conditions.

Increase System Size

The FSII-BP24 can be mixed with FSII-BP19 on the same system, increasing the quantity of beltack users in a single radio space. In the US, between 50 – 65 users can operate on a single system, while the rest of the world can have between 70 - 90 users in the same radio space.

Durability

The FSII-BP24 are IP-65 rated for wet weather or dusty conditions making them ideal for outdoor productions. For better grip and protection, the beltacks have a rubberized over-mold to protect from the most rugged environments.

Battery Life and Charging

Using the BAT60 Li-Ion battery, the FSII-BP24 has 18+ hours of battery life. Using an alternative set of 3 AA cells, the battery life is 6-9 hours. The beltacks also include an USB charging port for recharging or for continuous powered transmissions.

ComtronICS

2350 Fortune Drive
Lexington KY 40509
www.comtronicsnow.com
Voice: 1.800.264.6021 or +1.859.299.9494
Fax: 1.859.299.9334

Manufactured and sold exclusively by Clear-Comm, LLC



Technical Specifications

Audio

Audio Bandwidth: 200Hz-7.5KHz
 No. of Full-Duplex Audio Paths: Up to 5 with individual level control (2 dedicated rotaries, 3 with menu), 2 controls and a main volume
 Mode of Operation: Full duplex on all routes
 Level/Talk Controls: 4 pushbuttons, a reply button and 2 rotary controls
 Enter/Answer-Back Button: 1

Radio

Frequency Spectrum: 2.400-2.483MHz for EU and US cellular auto roaming technology
 Modulation: GFSK, TDMA frame 10ms full slot
 Output power: (EU) 18dBm, (RoW) 22dBm
 Range: Up to 1475ft (450m) in good radio frequency conditions, 800 feet typical
 Battery: Li-Ion or 3 AA alkaline cells
 Battery Charging: Drop-in charger (AC60) or local USB
 Battery Life: 18+ hours with Li-Ion; 9 hours with 3 x Alkaline AA cells

Headset Connector: 4-pin male, Clear-Com standard, options for 5-pin female and 7-pin male with PTT
 Microphone Type: Electret and Dynamic, selectable in beltpack menu
 Headset Limiter: Selectable from beltpack menu

Environmental

IP-65 water and dust resistance
 -67°F to +158°F
 (-55°C to +70°C)

Dimensions

Tapered design at largest points
 5 x 1.5 x 3.75in
 (130 x 45 x 97mm) (DxWxH)

Weight

9.0 oz (0.4kg) including batteries



Beltpack Legend

1. Volume Control
2. Power Button
3. Reply Button
4. Menu Button
5. Shoulder Strap Hook
6. Belt Clip
7. Battery Door
8. Channel A
9. Channel C
10. LCD
11. Channel D
12. Channel B
13. Flashlight
14. Flashlight Switch
15. Headset Connector
16. USB and Audio Jack Connectors

Order Codes

Part Number and Description

FSII-BP24-X4: Beltpack with XLR-4M headset connector, approved for use in USA, Canada and world wide sales except EU

FSII-BP24-X5: Beltpack with XLR-5F headset connector, approved for use in USA, Canada and world wide sales except EU

FSII-BP24-X7: Beltpack with XLR-7M headset connector, approved for use in USA, Canada and world wide sales except EU

FSII-BP24-X4-EU: Beltpack with XLR-4M headset connector, approved for use in the EU only

FSII-BP24-X5-EU: Beltpack with XLR-5F headset connector, approved for use in the EU only

FSII-BP24-X7-EU: Beltpack with XLR-7M headset connector, approved for use in the EU only

Available from



800.264.6021 | comtronicsnow.com

Notice About Specifications

While Clear-Com makes every attempt to maintain the accuracy of the information contained in its product manuals, that information is subject to change without notice. Performance specifications included in this manual are design-center specifications and are included for customer guidance and to facilitate system installation. Actual operating performance may vary.