

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to you or to others, you are encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. To maintain compliance with FCC RF exposure compliance requirements, please avoid direct contact to the transmitting antenna during transmitting.

RF Exposure Warning!

This device contains transmitters and receivers which emit Radio Frequency (RF) energy. The device is designed to comply with the limits for exposure to RF energy set by the Federal Communications Commission (FCC) of the United States, Industry Canada (IC) or Canada, and the regulating entities of other countries.

If you are still concerned about exposure to RF energy, you can further limit your exposure by limiting the amount of time you use the equipment or by placing more distance between your body and the device, since exposure level drops off dramatically with distance.

2350 Fortune Drive, Lexington KY 40509
 PH: 859.299.9494 FAX: 859.299.9334
 TOLL FREE: 800.264.6021
 WWW.COBALTAV.COM

Version 1.00 July 2017



AMPS-BLUE-KU
 Wireless Bluetooth Speaker Microphone

For use with Android and Apple iOS smart devices using the AT&T ePTT app



Model No. AMPS-BLUE-KU

Cobalt AV and AMPS-BLUE-KU are trademarks owned by Cobalt Audio Video, Lexington KY. All other product or service names are the property of their respective owners.

© 2017 Cobalt Audio Video, Lexington KY. All Rights Reserved

Controls and Connection

Front Firing Speaker

Received calls are heard over this speaker. The volume level can be controlled using either the Volume Up / Down buttons on the speaker microphone, or by using the volume controls on the phone.

Microphone:

This microphone picks up the user's voice audio when sending a call

PTT Button

This button is used to activate the push-to-talk feature of the AT&T ePTT app.

Clothing Clip

The alligator-type clip secures the speaker microphone to the user's clothing during use. The clip can be rotated to allow the microphone to be better positioned.

Phone Button

This button can be used to answer or hang up phone calls.

Earphone Jack

This jack is used to connect an (optional) wired listen-only earphone to the speaker microphone for enhanced privacy.

Charge Jack

This mini-USB jack is used to recharge the removable battery of the speaker microphone by connecting the AMPS-BLUE-KU to a USB charger or any powered USB source.

Multifunction Button

Holding down this button for one second will turn the speaker microphone on and off. This button can also be used to place the speaker microphone into pairing mode so that it can be connected wirelessly to a cellular phone.

Volume Up and Down Buttons

These buttons can be used to turn the receive audio volume of the speaker microphone up or down in five preset steps.

Status LEDs

The red and blue LEDs flash messages that let the user know the current status of the speaker microphone.

Battery Cover

The rear cover of the speaker microphone can be removed by loosening the thumbscrew on the rear of the microphone. This allows the user to gain access to the removable battery pack.

Removable Battery

The speaker microphone is powered by a removable Lithium battery pack.



Charging the Speaker Microphone

The AMPS-BLUE-KU speaker microphone has a replaceable Lithium Ion rechargeable battery pack which must be charged prior to operation, and must be recharged regularly. A fully charged battery will provide up to 40 hours of continuous operation before needing to be recharged. However, operating time can vary depending on usage and the condition of the battery pack. Recharge the battery regularly.



To charge the speaker microphone

1. Ensure the device is turned off using the multifunction button.
2. Plug the charge cable into any powered USB outlet, such as an AC wall charger, and then into the charge jack on the speaker microphone.
3. Once the charging process has begun, the LED indicator on the bottom of the speaker microphone will show a constant red light.
4. Typical charge time is approximately five hours. Actual charge time will vary depending on several factors including the battery's charge state, condition, and age.
5. When the battery is fully charged the LED indicator on the speaker microphone will turn off.
6. Disconnect the charger from the adapter when charging is completed.

Charging Cautions:

- Do not use a wall charger or charge cable that appears to be damaged. (Example: frayed wires, melted plastic, etc.) Contact Cobalt AV to get a new manufacturer-approved replacement charger.
- Do not tamper with or modify the speaker microphone or charger.
- Always turn the speaker microphone off when charging.

Installing or Replacing the Battery Pack

The AMPS-BLUE-KU Bluetooth speaker microphone gets its power from a rechargeable Lithium-Ion type battery pack. The battery pack must be installed inside the microphone prior to operation. Under normal usage, this battery should have a lifespan of over 1,500 charge/discharge cycles before needing to be replaced.



To access the battery compartment:

1. Rotate the clothing clip on the back of the speaker microphone 90° to expose the thumbscrew at the top of the battery compartment cover. Rotate the thumbscrew counter-clockwise until the cover opens. Remove the battery door.
2. Insert the rechargeable battery pack into the battery compartment. Ensure that the battery terminals are properly lined up with the contacts inside of the battery compartment.
3. Reinstall the battery compartment cover and rotate the thumbscrew clockwise to tighten. Do NOT over tighten.

PAIRING THE AMPS-BLUE-KU SPEAKER MICROPHONE WITH A CELL

The AMPS-BLUE-KU speaker microphone is designed to work with smart devices running either the Android or Apple iOS operating systems. Prior to normal operation, the phone and speaker microphone must be paired together using the following process (note the process for iOS and Android are different):



To pair the AMPS-BLUE-KU speaker microphone with an Android phone:

1. When pairing the speaker microphone with an Android phone, first make sure that the AMPS-BLUE-KU and all other nearby Bluetooth devices are powered off before beginning.
2. Press and hold down the Power Button on the AMPS-BLUE-KU for five seconds, until the LED on the speaker microphone flashes RED-BLUE-RED-BLUE continuously in sequence. The BTH-600-KU speaker microphone is now in pairing mode.
3. Activate the Bluetooth feature on your phone.
4. Activate the "scan/discover new Bluetooth devices" feature on the phone. The exact steps needed to do this will vary depending on the brand/model of phone you are using.
5. Select the BTH-600-KU from the list of Bluetooth devices shown on your phone. If the phone asks for a passcode, enter "0000". The phone may also prompt you to confirm the connection.
6. After a few seconds, the two devices should synch to one another. Once the AMPS-BLUE-KU speaker microphone and phone are paired with each other, the status LED on the microphone will revert back to a single blue flash every few seconds.
7. Once successfully paired, you will be able to make and receive phone calls using the AMPS-BLUE-KU speaker microphone.

To pair the AMPS-BLUE-KU speaker microphone with an Apple iOS phone:

1. When pairing the speaker microphone with a Apple iOS phone, first make sure that the AMPS-BLUE-KU and all other nearby Bluetooth devices are powered off before beginning.
2. Press and hold down the Power Button on the AMPS-BLUE-KU for five seconds, until the LED on the speaker microphone flashes RED-BLUE-RED-BLUE continuously in sequence. The AMPS-BLUE-KU speaker microphone is now in pairing mode.
3. Activate the Bluetooth feature on your phone.
4. In the phone's Bluetooth list, two devices will be found, "BTH-600" and "PTT-U." Both of these Bluetooth devices must be paired to the phone for the AMPS-BLUE-KU's audio and push-to-talk features to work.
5. Tap on "BTH-600" to pair the phone with the Bluetooth audio. If the phone asks for a passcode, enter "0000". The phone may also prompt you to confirm the connection.
6. After a few seconds, the two devices should synch to one another. Once the AMPS-BLUE-KU speaker microphone and phone are paired with each other, the status LED on the microphone will revert back to a single blue flash every few seconds.
7. Tap on "PTT-U" to pair the phone with the push-to-talk connection. The phone may also prompt you to confirm the connection.
8. Once successfully paired, you will be able to make and receive phone calls using the AMPS-BLUE-KU speaker microphone.

Reconnecting a Previously Paired Speaker Microphone and Radio Adapter/Cellular Phone

Once the AMPS-BLUE-KU speaker microphone and Bluetooth radio adapter and/or cellular phone have been successfully paired together, both devices will remember that connection. The speaker microphone and radio adapter/phone will attempt to reestablish their link whenever they are both powered on and in within range of each other. Re-establishing this connection can take 10-60 seconds.

OPTIONAL EAPRHONES

Although the AMPS-BLUE-KU has a built-in speaker for listening to received calls, some users may prefer to use a listen only earphone for enhanced privacy. The accessory jack on the speaker microphone will accept any mono earphone with a 3.5 mm audio plug. When an earphone is used, the front-firing speaker is disabled.

Cobalt AV KLSH model shown.
(Earphone sold separately.)



Cobalt AV makes a variety of listen-only earphones in different styles that work with the AMPS-BLUE-KU.

Model	Model	Cable Length/Type	Connector
KLSC-S3.5	Rubber Ear Hook	15" Coiled	3.5mm right angle
KLSC-L3.5	Rubber Ear Hook	25" Coiled	3.5mm right angle
KLEL-S3.5	Plastic D-Ring	15" Coiled	3.5mm right angle
KLEL-L3.5	Plastic D-Ring	25" Coiled	3.5mm right angle
KLSH-S3.5	Acoustic Tube	15" Coiled	3.5mm right angle
KLSH-L3.5	Acoustic Tube	30" Straight	3.5mm right angle
	Acoustic Tube	30" Straight	3.5mm right straight
GLSH-S3.5	G-Hook (swivel)	10" Coiled	3.5mm right angle

SPECIFICATIONS

Bluetooth Version:	v3.0+EDR, BTLE
Speaker Output:	1 watt
Receiver Sensitivity:	-82 dBm (typ.)
Power Class:	Bluetooth class 2
Range:	10 meters
Display:	Blue and Red
Bluetooth Profile:	HSP, HFP, AzDP, AVRCP, SPP
Operating Voltage:	5 VDC
Battery Capacity:	1,020 mAh
Operating Time (Standby):	> 30 days
Operating Time (Typical):	> 80 hours
Operating Time (Continuous Talk):	> 40 hours
Push-to-Talk Function:	built-in
Operating Temperature:	-70°F to +120°F (approx.)

Setting up AT&T Enhanced PTT

To get the AT&T ePTT app on your phone and set it up to work with the AMPS-BLUE-KU's speaker microphone do the following:

1. Install the AT&T ePTT app onto your phone using the Google Play Store
2. Launch the AT&T ePTT app.
3. Accept the End User License Agreement for the app.
4. When prompted, select "Yes" to activate the app.
5. Log in with your AT&T account.



Using the Speaker Microphone with AT&T ePTT

Once setup, you will be able to use the speaker microphone with the AT&T ePTT app, even if ePTT is running the background.

- To activate ePTT's push-to-talk feature, press and hold the PTT button on the speaker microphone.
- When ePTT is transmitting a call, audio will be picked up by the BTH-600-KU's built-in microphone unless a wired accessory with a built-in microphone is plugged into the speaker microphone. In that case, the accessory microphone will be used instead.
- Incoming calls received by ePTT will be heard over the earphone that is plugged into the AMPS-BLUE-KU's accessory port.

Making and Receiving Phone Calls

You can also use the speaker microphone to make and receive phone calls.

- You can initiate a phone call by using the Phone Dialer app in the phone.
- Phone audio will be routed to the AMPS-BLUE-KU's accessory port and microphone.
- To answer an incoming call, press the phone button on the speaker microphone.
- While on a call, you can press the phone button on the speaker microphone to hang up the phone and end the call.

Phone functions are provided by using the AMPS-BLUE-KU's Phone Button.

Call State	Button Press	Function
Incoming call	Press Phone Button once	Answer call
Incoming call	Press and hold Phone Button for 5 seconds	Reject call
On a call	Press Phone Button once	Hang up call
No call	Long press Phone Button	Activate voice dialer

STATUS LED MESSAGES

The meanings of the various status LED messages shown by the speaker microphone are shown on the following table:

LED INDICATION	MEANING
Constant Red (while plugged into charger)	Charge mode
No indication (while plugged into charger)	Charging is finished
Flashes red-blue-red-blue repeatedly	Pairing mode
Two blue flashes every two seconds	Speaker microphone is powered on but not paired
Three blue flashes every two seconds	Speaker microphone is powered and paired
Constant red with one blue flash every two seconds	PTT is pressed
No indication	Speaker microphone is powered off

SUPPORT AND WARRANTY

Cobalt Audio Video warrants this product against defects in materials or workmanship for a period of one year from the date of retail purchase. Cobalt AV will repair or replace a defective unit, at our option, without charge for parts or labor. The limited warranty is extended only to the original purchaser and is valid only to consumers in the United States and Canada. It does not cover damage or failure caused by or attributable to Acts of God, abuse, misuse, improper or abnormal usage, faulty installation, improper maintenance, lightning, or other incidences of excessive voltage, or any tampering or repairs by other than a Cobalt AV authorized repair facility. It does not cover replacement of consumable parts, transportation costs, or damage in transit.

Repair or replacement under the terms of this warranty does not extend the terms of this warranty. This warranty can only be modified by an officer of Cobalt AV, and then only in writing. Should this product prove defective in workmanship or material, the consumer's sole remedies shall be such repair or replacement as provided by the terms of this warranty. Under no circumstances shall Cobalt AV be liable for any loss or damage, direct, consequential, or incidental, arising out of the use of or inability to use this product. Some states do not allow limitations on how long an implied warranty lasts or the exclusions or limitations of incidental or consequential damages, so the above limitations or exclusions may not apply to you. This warranty gives you specific legal rights. You may also have other rights, which may vary, from state to state.

For support or warranty service on your Cobalt AV product, contact us at 1-800-264-6021 or visit us on the web at www.cobaltav.com.

COPYRIGHT AND TRADEMARK INFO

© 2017 Cobalt Audio Video, Lexington KY. All rights reserved.

Cobalt AV and AMPS-BLUE-KU are trademarks owned by Cobalt Audio Video, Lexington KY.

Android is a trademark of Google Inc.

Apple is a trademark of Apple Inc.

iOS is a trademark of Cisco Systems and is used by Apple Inc. under license.

AT&T is a trademark of AT&T Intellectual Property and/or AT&T allied companies.

All other product or service names are the property of their respective owners.

DISCLAIMER: The Bluetooth wireless link used by Cobalt AV products is an open standard, unsecured technology. As such, it is not recommended for first-responder or other mission critical users.